

Solenne Floor 360/506 LED CASAMBI 3000K

Solenne is designed by Kauppi & Kauppi and includes a total of seven lighting fixtures, all with generous matt opal glass shades and black or white glazed porcelain bases. Four of the fixtures follow our traditional range for ceiling, wall, and facade with IP44 ratings suitable for both indoor and outdoor installations. The collection also includes three more novel types of lighting fixtures, taking our pressed porcelain to new indoor contexts. Solenne includes a grand pendant with a corresponding porcelain ceiling cup, a new table luminaire with a wooden base, and Ifö Electric's very first floor lamp.

| | |
|------------------|---------------|
| EAN / GTIN | 7312908413961 |
| E-number | 7509665 |
| Article no. | 8413-8062-16 |
| Type designation | 8413/CASAMBI |



Specification

| | |
|--------------------|----------------------|
| Base colour | Black (NCS S 9000-N) |
| Glass | Matt opalglas |
| Glass thread (mm) | 184 mm |
| Glass gasket | Silicone |
| Diameter (mm) | 360 |
| Height (mm) | 506 |
| Lamp holder | LED |
| Light source | LED module, 10W ** |
| Colour temperature | 3000K |
| MacAdam | 3 SDCM |
| Life span | L80/B10: 47 000 h |
| Ra | Min 90 |
| Lighting control | LED module, 10W ** |
| Rated voltage | 230V |
| Dimmable | Casambi |
| IP class | IP20 |
| Insulation class | I |
| Energy class | E |
| D class | No |
| IK class | IK02 |
| Ta | -30 - +25 |
| Installation | Floor luminaire |
| Bridging | No |
| Connection | EU plug class I |
| Family | Solenne |
| Design | Kauppi & Kauppi |



Maintenance

Disconnect the luminaire. Remove the shade and clean it. Do not use cleaning agents containing solvents. Change the light source if necessary. Check the gasket and change it if necessary. Replace the shade.

Spare parts

Shade Solenne 360, Article no.: 1-6166-30
Gasket silicone for bayonett 184mm, Article no.: 1-03397

*** The device must under no circumstances be connected to the same phase as a magnetic ballast or other older fluorescent luminaires as these luminaires can generate overvoltage transients outside of EU regulatory standards when switched off or on. The luminaire can permanently damage or completely cease to function when connected.*

If the luminaire is modified the person responsible for the modification shall be considered manufacturer. Subject to errors in text. We reserve the right to change the technical specifications (without notice).